

Designed by Louis Weisdorf

PRODUCT



COLORS





// All brass

// Black/ Brass



// White/ Chrome

DESCRIPTION

The Multi-Lite was first drawn in 1972 when Louis Weisdorf did an exception to his own design custom of using multiple repeating elements. Instead it reflects his passion for diversity. The Multi-Lite Floor lamp has two individual rotating shades and can be transformed into multiple combinations where the light can be directed upwards, downwards or exude an assymetrical art light. The lamp is available in different colors and all the shades are white lacquered inside.

VERSION - MULTI-LITE TABLE


Colour codes are indicative:

All Brass - Brass colored cable, Brass foot switch, Black plug
Brass/Charcoal Black - RAL 9011 - Gloss level 5 - Brass cable, Brass foot switch, Black plug
Chrome/White - RAL 9003 - Gloss level 15 - Black cable, Black foot switch, Black plug

Base and centerpole:

- Brass on brass versions
- Chrome on chrome versions

MEASUREMENTS



FACTS

MEASUREMENT - L x W x H mm

Lamp height: 500 mm Lamp diameter: Ø255 mm Wire length, exposed: Approx: 2000 mm

WEIGHT ITEM - $LAMP\ INCL.\ WIRE\ 2750\ g$

PACKAGING TYPE Cardboard box

PACKAGING MEASUREMENT - L x W x H cm

L: 58 x W: 27 x H: 30

WEIGHT PACKAGING - MATERIAL TYPE (recycleable)

- Polystyrene: 380 g - PE polybag: 60 g
- PE polybag: 60 (
- Cardboard: 810

WEIGHT PACKAGING - *TOTAL* 1250 g

NUMBER OF PARCELS

1 pcs.



Designed by Louis Weisdorf

ACCESSORIES

ENVIRONMENT

TESTS

CERTIFICATION AND LABELS

CE-certified

SAFETY INSTRUCTIONS

If the cord or other electrical part is damaged, switch of the lamp and do not use it until it is repaired by a qualified electrician.

INSTALLATION INSTRUCTIONS

Instructions document no. 58-20-010-02

CARE INSTRUCTIONS

TROUBLESHOOTING

TECHNICAL INFORMATION
Light sources: E14, 470 Lumes |s 40W incondenced, s20W lettinger, 0-40W LED Dimension). The prover off when changing light builb. lielaking dates. The lamp in ord approved for authors or use in disproved forms (2004).

1

does not light, turn off the power. Check the bulb for a broke int. Replace bulb if necessary, there turn it on. If the lamp still of light, please contact masterner service at the local dealer, it enter through patch or cond of this lamp is damaged, it must be faced by a qualified electrical in order to send a heard.





ASSEMBLY INSTRUCTIONS Multi-Lite Table Lamp



LIGHT SOURCE:

- Socket: E14 base
- Bulb types recommended:



- Recommended light sources:

470 Lumen (≤ 30W halogen, ~ 4-6W LED Dimmable)

- Max. light out put for above lamps:

(≤ 40W incandescent ≤ 30W halogen, ~ 5-6W LED Dimmable

- Best result is achieved with frosted light bulbs with a CRI (Colour Rendering Index) larger than 90.
- Lightbulb not included.
- All lamps can be fitted with a dimmer.
- Please contact your local electrician.

*Euro voltage: 230 V

*Freqvency: 50 Hz

*Supply voltage: AC power ~

*Normally Closed: IP20







Class II / Double insulated



GUBI

ASSEMBLY INSTRUCTIONS

MULTI-LITE FLOOR LAMP





